N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

### **G<u><u><u></u></u>INSTEK**</u>

### **GDS-3000A Specifications**

The specifications apply when the GDS-3000A series is powered on for at least 30 minutes under

+20°C~+30°	C.	
GDS-3352A	Channels	2 + Ext
	Bandwidth	DC ~ 350MHz (-3dB) @50Ω/1MΩ input impedance
	Rise Time	1ns (calculated)
	Bandwidth Limit	20MHz/100MHz/200MHz*
GDS-3652A	Channels	2 + Ext
0200002	Bandwidth	DC ~ 650MHz (–3dB) @50Ω input impedance
	Banamaan	DC ~ 500MHz ( $-3$ dB) @1M $\Omega$ input impedance
	Rise Time	535ps (calculated)
	Bandwidth Limit	20MHz/100MHz/200MHz/300MHz*
* The tolerand	e of bandwidth limit is ±	
Vertical	Resolution	8 bits (Max.12bits with Hi Res)
Sensitivity		For 1M $\Omega$ input impedance: 1mV*~10V/div
		For 50Ω input impedance: 1mV*~1V/div
	Input Coupling	AC, DC, GND
	Input Impedance	1MΩ// 22pF approx.
	DC Gain Accuracy	1mV: ±5% full scale
	<b>-</b>	≥2mV: ±3% full scale
	Polarity	Normal & Invert
	Maximum Input	For 1M $\Omega$ input impedance: 300Vrms, CAT II
	Voltage	For 50Ω input impedance: 5Vrms max.
	Offset Position Range	For $1M\Omega$ input impedance:
		1mV/div ~ 20mV/div :±1V; 50mV/div ~ 500mV/div: ±10V
		1V/div ~ 5V/div : ±100V; 10V/div : ±1000V
		For $50\Omega$ input impedance:
		1mV/div ~ 50mV/div:±1V; 100mV/div ~ 1V/div : ±10V
	Waveform Signal	+, -, x, ÷, FFT, User Defined Expression
	Process	FFT: Spectral magnitude. Set FFT Vertical Scale to Linear RMS or dBV RMS, and
<del></del> .	2	FFT Window to Rectangular, Hamming, Hanning or Blackman.
Trigger	Source	CH1, CH2, Line, EXT
Trigger	Trigger Mode	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single
Trigger		CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout,
Trigger	Trigger Mode	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus
Trigger	Trigger Mode Trigger Type	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN)
Trigger	Trigger Mode Trigger Type Holdoff range	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s
Trigger	Trigger Mode Trigger Type Holdoff range Coupling	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej.
	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div
External	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V
	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV
External	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV
External Trigger	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF
External Trigger *: The bandwi	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div.
External Trigger	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments)
External Trigger *: The bandwi	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range	CH1, CH2, Line, EXTAuto (supports Roll Mode for 100ms/div and slower), Normal, SingleEdge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN)4ns to 10sAC, DC, LF rej., HF rej., Noise rej.1div±20VDC ~ 100MHz Approx. 100mV100MHz ~ 350MHz Approx. 150mV1MΩ±3%~22pFat 1mV/div and 2mV/div.1ns/div ~ 1000s/div (1-2-5 increments)ROLL: 100ms/div ~ 1000s/div
External Trigger *: The bandwi	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum
External Trigger *: The bandwi	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum.
External Trigger *: The bandwi Horizontal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel;
External Trigger *: The bandwi Horizontal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode Peak Detection	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single 400ps (typical)
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode Peak Detection Average	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single 400ps (typical) Selectable from 2 to 256
External Trigger *: The bandwi Horizontal Signal Acquisition	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode Peak Detection Average Number of Segments	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single 400ps (typical) Selectable from 2 to 256 1 to 490,000 maximum
External Trigger *: The bandwi Horizontal Signal	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode Peak Detection Average Number of Segments X-Axis Input	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single 400ps (typical) Selectable from 2 to 256 1 to 490,000 maximum Channel 1
External Trigger *: The bandwi Horizontal Signal Acquisition	Trigger Mode Trigger Type Holdoff range Coupling Sensitivity Range Sensitivity Input Impedance dth is limited to 20MHz Time base Range Pre-trigger Post-trigger Time base Accuracy Real Time Sample Rate Record Length Acquisition Mode Peak Detection Average Number of Segments	CH1, CH2, Line, EXT Auto (supports Roll Mode for 100ms/div and slower), Normal, Single Edge, Pulse Width(Glitch), Video, Pulse Runt, Rise & Fall(Slope), Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4ns~10s), Bus (UART, I2C, CAN, LIN) 4ns to 10s AC, DC, LF rej., HF rej., Noise rej. 1div ±20V DC ~ 100MHz Approx. 100mV 100MHz ~ 350MHz Approx. 150mV 1MΩ±3%~22pF at 1mV/div and 2mV/div. 1ns/div ~ 1000s/div (1-2-5 increments) ROLL: 100ms/div ~ 1000s/div 10 div maximum 10,000,000 div maximum. ±5 ppm, about ±2ppm increase in error per year 5GSa/s one channel; 2.5GSa/s dual channels Max. 200Mpts /CH Normal, Average, High Resolution, Peak Detect, Single 400ps (typical) Selectable from 2 to 256 1 to 490,000 maximum

GOOD WILL INSTRUMENT CO., LTD.

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

Cursors and Measurement	Cursors	Amplitude, Time, Gating available;
	Automatic Measurement	Unit: Seconds(s), Hz (1/s), Phase (degree), Ratio (%). 38 sets with indicator: Pk-Pk, Max, Min, Amplitude, High, Low, Mean, Cycle Mean, RMS, Cycle RMS, Area, Cycle Area, ROVShoot, FOVShoot, RPREShoot, FPREShoot, Frequency, Period, RiseTime, FallTime, +Width, -Width, Duty Cycle,
		+Pulses, -Pulses, +Edges, -Edges, %Flicker, Flicker Idx ,FRR, FRF, FFR, FFF, LRR, LRF, LFR, LFF, Phase.
	Cursors measurement	Voltage difference between cursors( $\Delta V$ ) Time difference between cursors( $\Delta T$ )
	Auto counter	6 digits, range from 2Hz minimum to the rated bandwidth
Control Panel Function		Single-button, automatic setup of all channels for vertical, horizontal and trigger systems, with "Undo Autoset", "Fit Screen"/ "AC Priority" mode, and "Fine Scale" functions.
	Save Setup	20 sets
	Save Waveform	20 sets
	Save Reference Waveform	4 sets
Power		nics, Ripple, In-rush current, Switching Loss, Modulation, SOA, Transient,
		op Response, Efficiency, PSRR, Turn On/Off
AWG	General	
	Channels	2
	Sample Rate	200MSa/s
	Vertical Resolution	14 bits
	Max. Frequency	25 MHz
	Waveforms	Sine, Square, Pulse, Ramp, DC, Noise Sinc, Gaussian, Lorentz, Exponential Rise, Exponential Fall, Haversine, Cardiac
	Output Range	20 mVpp to 5 Vpp, HighZ; 10 mVpp to 2.5 Vpp, 50Ω
	Output Resolution	1mV
	Output Accuracy	2% (1 kHz)
	Offset Range	±2.5V(DC+AC), HighZ; ±1.25 V(DC+AC), 50 Ω
	Offset Resolution	1mV
	Sine	
		100 mHz to 25 MHz
	Flatness	±0.5 dB < 15MHz;
	(relative to 1 kHz)	±1dB 15MHz~25MHz
	Harmonic Distortion	-40 dBc
	Stray (Non-harmonic)	-40 dBc
	Total Harmonic Distortion	1%
	S/N Ratio	40 dB
	Square/Pulse	
	Frequency Range	Square: 100 mHz to 15 MHz
	Rise/Fall Time	< 15ns
	Overshoot	< 3 %
	Duty Cycle	Square: 50% Pulse: 0.4% to 99.6%
	Min. Pulse Width	30ns
	Jitter	500 ps
	Ramp	
	Frequency Range	100 mHz to 1MHz
	Linearity	1%
	Symmetry	0 to 100%
Spectrum Analyzer	Frequency Range	DC~2.5GHz Max, dual channel with spectrogram (based on Advanced FFT). Notice: Frequency which exceeds analog front end bandwidth is uncalibrated
	Span	1kHz~2.5GHz (Max.)
	Resolution Bandwidth	
	Reference Level	-80dBm to +40dBm in steps of 5dBm

**G<u><u><u></u></u>INSTEK**</u>

#### GOOD WILL INSTRUMENT CO., LTD.

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

# **G<u><u><u></u></u>INSTEK**</u>

	Vertical Units	dBV RMS; Linear RMS; dBm
	Vertical Position	-12divs to +12divs
	Vertical Scale	1dB/div to 20dB/div in a 1-2-5 Sequence
	Displayed Average	1V/div ← -40dBm, Avg :16
	Noise Level	$100 \text{mV/div} \leftarrow -60 \text{dBm}, \text{Avg}: 16$
		10mV/div ← -80dBm, Avg :16
	Spurious Response	2nd harmonic distortion < 35dBc
	-1	3rd harmonic distortion < 40dBc
	Frequency Domain	Normal; Max Hold; Min Hold; Average (2 ~ 256)
	Trace Types	
	Detection Methods	Sample; +Peak; -Peak; Average
	FFT Windows	FFT Factor:
		Hanning 1.44
		Rectangular 0.89
		Hamming 1.30
		Blackman 1.68
Logic	Sample Rate	1GSa/s
Analyzer	Bandwidth	200MHz
(Option)	Record Length	Per Channel 10M points (max)
	Input Channels	16 Digital (D15 - D0)
	Trigger type	Edge, Pattern, Pulse Width, Serial bus (I2C,SPI, UART, CAN, LIN), Parallel Bus
	Thresholds Quad	Settable thresholds for:
	<b>T</b> I I I I I <i>I</i>	D0-D3, D4-D7, D8-11, D12-15
	Threshold selections	TTL, CMOS(5V,3.3V,2.5V), ECL, PECL,0V ,User Defined
	User-defined	±5V
	Threshold Range	. 40.1/
	Maximum Input Voltage	±40 V
	Minimum Voltage Swing	±250 mV
	Vertical Resolution	1 bit
Frequency	Frequency Range	20Hz to 25MHz
Response	Input and Output	Channel 1 ~ 2
Analyzer	Sources	
	Number of Test	10, 15, 30, 45, 90 points per decade selectable for logarithm scale;
	Points	2 ~ 1000 points selectable for linear scale
	Dynamic Range	> 80dB (typical)
	Test Amplitude	10mVpp to 2.5Vpp into 50 $\Omega$ , 20mVpp to 5Vpp into High-Z, Fixed test amplitude or
		custom amplitude for each decade.
	Test Results	Logarithmic or linear overlaid gain and phase plot, may also overlay with reference plots for cross comparison. Test results saved in csv format for offline analysis.
	Manual	Tracking gain and phase markers
	Measurements	
	Plot Scaling	Auto-scaled during test
Display	TFT LCD Type	10.2" TFT LCD WVGA color display
. ,	Display Resolution	800 horizontal × 480 vertical pixels (WVGA)
	Interpolation	Sin(x)/x
	Waveform Display	Dots, vectors, variable persistence (16ms~4s), infinite persistence, gray or color
	Movoform Undete	waveforms.
	Waveform Update Rate	200,000 waveforms per second, maximum
	Display Graticule	8 x 10 divisions
	Display Mode	YT, XY
Interface	USB Port	USB 2.0 High-speed host port X1, USB High-speed 2.0 device port X1
	Ethernet Port (LAN)	RJ-45 connector X1, 10/100Mbps with HP Auto-MDIX
	Go-NoGo BNC	5V Max/10mA open collector output X1
	Power Supply	±12V / 600mA for current probe use.
	Receptacles	Two sets of power supply receptacles.
	RS232C	DB-9 male connector X1
	VGA Video Port	DB-15 female connector X1, monitor output for display on VGA monitor
	Optional GPIB	Fully programmable with IEEE488-2 compliance
	Module	

#### GOOD WILL INSTRUMENT CO., LTD.

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

	Kensington Style Lock	Rear-panel security slot connects to standard Kensington-style lock.
Miscellaneous I	Nulti-language menu	Available
	Operation Environment	Temperature: 0°C to 50°C. Relative Humidity $\leq$ 80% at 40°C or below; $\leq$ 45% at 41°C ~ 50°C.
C	On-screen help	Available
7	Time clock	Time and Date, Provide the Date/Time for saved data
Ī	nternal Flash Disk	800M bytes Single-Level Cell flash memory
Ī	nstalled APP	Go/NoGo, DVM, DataLog, Digital Filter, Frequency Response Analyzer, Mask, Mount Remote Disk, Demo
l	User Define Key	User can select one of the several different preset functions as shortcut key.
Ī	ine Voltage range	AC 100V ~ 240V, 50Hz ~ 60Hz, auto selection. power consumption:100W
N	Weight	Approx. 4.6kg
Ī	Dimensions	420mm(W)X 253mm(H)X 113.8mm(D)

# **G<u><u><u></u></u>INSTEK**</u>